

## US ROBOTICS 56K FAX/MODEM NOTES

### PROGRAMMING CABLE FOR DL3000:

9 PIN FEMALE            9 PIN FEMALE

2-----3  
3-----2  
5-----5

### PROGRAMMING CABLE FOR MODEM:

9 PIN FEMALE            25 PIN MALE

2-----3  
3-----2  
4-----20  
5-----7  
6-----6  
7-----4  
8-----1  
9-----22

TO PROGRAM FOR DL3000: SET DIP SWITCHES 3, 5 & 8 DOWN

ENTER THE FOLLOWING: (EACH SHOULD REPLY OK)

AT&F0  
ATY0  
AT&B1&C1&D2&H1&K0&M0&N6&R1&S1&W0  
ATB0&W0  
ATS0=1&W0  
ATS13=1&W0  
ATS19=1&W0

TO RUN WITH DL3000: SET DIP SWITCH 3 DOWN

### DL3000 CHB TO USROBOTICS MODEM CABLE:

9 PIN FEMALE            25 PIN MALE

2-----3  
3-----2  
4-----20  
5-----7  
7-----4    connect pins 4 & 5 together  
8-----5